



Committed to **you**

ROLLING SHUTTER

EXTERNAL HZ RADIO RECEIVER



TO INTEGRATE THE RADIO INTO A ROLLING SHUTTER

- It equips wired motors with the SIMU-Hz radio technology, for a modernisation or new installation.
- **INTEGRATION:** directly into the roller shutter box on a universal bracket from 150 mm.
- **QUICK TO INSTALL:** connection to the motor is quick and easy, thanks to the terminal block.
- **COMPATIBLE** with all controls and automation of the SIMU-Hz range.

REFERENCE

DESCRIPTION	REFERENCE	
	x1	x10
Hz RECEIVER (for all wired motors)	2004873	2004872
Hz RECEIVER (for T5 AUTO and T5 E motors)	2004875	2004874

SPECIFICATIONS

POWER SUPPLY : 230 V - 50 Hz

AMBIENT TEMPERATURE OF USE : -30°C / +80°C

PROTECTION INDEX : IP 44

RADIO FREQUENCY : 433.42 MHz

COMPATIBILITY MOTOR : With T3.5 / T5 / T6 / DMI5 or DMI6 motors (ref. 2004873) (to be fitted with connection kit 9011670) and T5E / T5 AUTO (ref. 2004875)

TRANSMITTER COMPATIBILITY : The entire range of SIMU-Hz transmitters (maximum of 12 transmitters per receiver)

HZ RECEIVER FOR T3.5 / T5 / T6 / DMI5 OR DMI6 MOTORS (to be fitted with connection kit 9011670):

230V~50Hz

antenna

Quick connector without screws

3 m

0.2 m

① BLUE
② BROWN
③ BLACK
⊕ GREEN / YELLOW

230V - 50Hz
L
N
PE

Quick connector without screws

Connection box

HZ RECEIVER FOR T5E / T5 AUTO MOTORS

230V~50Hz

antenna

Quick connector without screws

3 m

0.2 m

① BLUE
② BROWN
⊕ GREEN / YELLOW

230V - 50Hz
L
N
PE

Quick connector without screws

Connection box

⊗ 0,55 Nm ± 0,1

ACCESSORIES

PRODUCT	DESCRIPTION	REFERENCE x 10
	Terminal block for T3.5 / T5 / T6 / DMI5 or DMI6 motors	9011670
	Box for terminal block - IP44	2005028
	Receiver clip (tunnel box mounting configuration)	9012820

70
YEARS'
EXPERIENCE

FRENCH
BRAND

INVENTOR
OF TUBULAR
MOTOR

100%
OF OUR CUSTOMERS
WOULD RECOMMEND
US

20 MILLION MOTORS
INSTALLED
WORLDWIDE

SIMU

ZONE INDUSTRIELLE LES GIRANUX
70100 ARC-LÈS-GRAY
FRANCE

www.simu.com

